SIEMENS

Data sheet

6ES7526-2BF00-0AB0



SIMATIC S7-1500, F digital output module, F-DQ 8x 24 V DC 2A PPM PROFIsafe; 35 mm width; up to PL E (ISO 13849-1)/ SIL3 (IEC 61508)

General information	
Product type designation	F-DQ 8x24VDC/2A PPM
Firmware version	
FW update possible	Yes
Product function	
• I&M data	Yes; I&M0 to I&M3
Engineering with	
 STEP 7 TIA Portal configurable/integrated from version 	V13 SP1 with HSP 0086
Operating mode	
• DQ	Yes
Supply voltage	
Rated value (DC)	24 V
permissible range, lower limit (DC)	19.2 V
permissible range, upper limit (DC)	28.8 V
Reverse polarity protection	Yes
Input current	
Current consumption (rated value)	110 mA; without load
Current consumption, max.	130 mA; without load
output voltage / header	
Rated value (DC)	24 V
Power	
Power available from the backplane bus	0.8 W
Power loss	
Power loss, typ.	11 W
Address area	
Address space per module	
Inputs	6 byte; S7-300/400F CPU, 5 byte
Outputs	6 byte; S7-300/400F CPU, 5 byte
Hardware configuration	
Automatic encoding	Yes
 Electronic coding element type F 	Yes
Digital outputs	
Number of digital outputs	8
Current-sinking	Yes
Current-sourcing	Yes
Short-circuit protection	Yes
Open-circuit detection	Yes
 Response threshold, typ. 	8 mA
Overload protection	Yes

- Despense threshold tur	201
Response threshold, typ. Limitation of industries about decrease to the second s	2.9 A
Limitation of inductive shutdown voltage to	PM-switching: -24 V + (-47 V), PP-switching: -24 V
Switching capacity of the outputs	0.4
with resistive load, max.	2 A
• on lamp load, max.	10 W
Load resistance range	10.0
• lower limit	12 Ω
• upper limit	2 000 Ω
Output voltage	
for signal "1", min.	24 V; L+ (-0.5 V)
Output current	
for signal "1" rated value	2 A
for signal "0" residual current, max.	0.5 mA; Current-sourcing, or current sourcing and sinking switches
	individually, current sinking: max. 1 mA
Switching frequency	
with resistive load, max.	30 Hz
 with inductive load, max. 	0.1 Hz
• on lamp load, max.	10 Hz
Total current of the outputs	
Current per channel, max.	2 A
Total current of the outputs (per module)	
horizontal installation	
— up to 40 °C, max.	16 A
— up to 60 °C, max.	8 A
vertical installation	
— up to 40 °C, max.	8 A
Cable length	
• shielded, max.	1 000 m
unshielded, max.	500 m
Interrupts/diagnostics/status information	
Diagnostics function	Yes
Substitute values connectable	No
Alarms	INC
Diagnostic alarm	Yes
Diagnoses	100
Monitoring the supply voltage	Yes
• Monitoring the supply voltage	165
	Voc
Wire-break	Yes
Wire-breakShort-circuit	Yes
Wire-breakShort-circuitGroup error	
 Wire-break Short-circuit Group error Diagnostics indication LED 	Yes Yes
Wire-break Short-circuit Group error Diagnostics indication LED RUN LED	Yes Yes; green LED
Wire-break Short-circuit Group error Diagnostics indication LED RUN LED ERROR LED	Yes Yes; green LED Yes; red LED
Wire-break Short-circuit Group error Diagnostics indication LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED)	Yes Yes; green LED Yes; red LED Yes
Wire-break Short-circuit Group error Diagnostics indication LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display	Yes Yes; green LED Yes; red LED Yes Yes; green LED
Wire-break Short-circuit Group error Diagnostics indication LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics	Yes Yes; green LED Yes; red LED Yes; green LED Yes; green LED Yes; red LED
Wire-break Short-circuit Group error Diagnostics indication LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics	Yes Yes; green LED Yes; red LED Yes Yes; green LED
Wire-break Short-circuit Group error Diagnostics indication LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics	Yes Yes; green LED Yes; red LED Yes; green LED Yes; green LED Yes; red LED
Wire-break Short-circuit Group error Diagnostics indication LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics	Yes Yes; green LED Yes; red LED Yes; green LED Yes; green LED Yes; red LED
Wire-break Short-circuit Group error Diagnostics indication LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics Potential separation	Yes Yes; green LED Yes; red LED Yes; green LED Yes; green LED Yes; red LED
Wire-break Short-circuit Group error Diagnostics indication LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics Potential separation Potential separation channels	Yes Yes; green LED Yes; red LED Yes; green LED Yes; green LED Yes; red LED Yes; red LED
Wire-break Short-circuit Group error Diagnostics indication LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics Potential separation Potential separation channels between the channels	Yes Yes; green LED Yes; red LED Yes; green LED Yes; green LED Yes; red LED Yes; red LED
Wire-break Short-circuit Group error Diagnostics indication LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics Potential separation Potential separation channels between the channels between the channels and backplane bus	Yes Yes; green LED Yes; red LED Yes Yes; green LED Yes; red LED Yes; red LED Yes; red LED No Yes
Wire-break Short-circuit Group error Diagnostics indication LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics Potential separation Potential separation channels between the channels between the channels and backplane bus Isolation Isolation	Yes Yes; green LED Yes; red LED Yes; green LED Yes; green LED Yes; red LED Yes; red LED
Wire-break Short-circuit Group error Diagnostics indication LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics Potential separation Potential separation Potential separation channels between the channels between the channels and backplane bus Isolation Isolation tested with Standards, approvals, certificates	Yes Yes; green LED Yes; red LED Yes; green LED Yes; green LED Yes; red LED Yes; red LED Yes; red LED No Yes 707 V DC (type test)
Wire-break Short-circuit Group error Diagnostics indication LED RUN LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics Potential separation Potential separation Potential separation channels between the channels between the channels and backplane bus Isolation Isolation tested with Standards, approvals, certificates Suitable for safety functions	Yes Yes; green LED Yes; red LED Yes Yes; green LED Yes; red LED Yes; red LED Yes; red LED No Yes
Wire-break Short-circuit Group error Diagnostics indication LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics Potential separation Potential separation channels between the channels between the channels and backplane bus Isolation Isolation Isolation tested with Standards, approvals, certificates Suitable for safety functions Highest safety class achievable in safety mode	Yes Yes; green LED Yes; red LED Yes; green LED Yes; green LED Yes; red LED Yes; red LED No Yes 707 V DC (type test) Yes
Wire-break Short-circuit Group error Diagnostics indication LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics Potential separation Potential separation Potential separation channels between the channels between the channels standards, approvals, certificates Suitable for safety functions Highest safety class achievable in safety mode Performance level according to ISO 13849-1	Yes Yes; green LED Yes; red LED Yes; green LED Yes; red LED Yes; red LED Yes; red LED No Yes 707 V DC (type test) Yes PLe
Wire-break Short-circuit Group error Diagnostics indication LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics Potential separation Potential separation channels between the channels between the channels between the channels substantion Isolation Isolation Isolation tested with Standards, approvals, certificates Suitable for safety functions Highest safety class achievable in safety mode Performance level according to ISO 13849-1 SIL acc. to IEC 61508	Yes Yes; green LED Yes; red LED Yes; green LED Yes; red LED Yes; red LED Yes; red LED No Yes 707 V DC (type test) PLe SIL 3
Wire-break Short-circuit Group error Diagnostics indication LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics between the channels and backplane bus Isolation Isolation tested with Standards, approvals, certificates Suitable for safety functions Highest safety class achievable in safety mode Performance level according to ISO 13849-1 SIL acc. to IEC 61508 Probability of failure (for service life of 20 years and reparation)	Yes Yes; green LED Yes; red LED Yes; green LED Yes; red LED Yes; red LED Yes; red LED No Yes 707 V DC (type test) PLe SIL 3 ir time of 100 hours)
Wire-break Short-circuit Group error Diagnostics indication LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics between the channels and backplane bus Isolation Isolation tested with Standards, approvals, certificates Suitable for safety functions Highest safety class achievable in safety mode Performance level according to ISO 13849-1 SIL acc. to IEC 61508 Probability of failure (for service life of 20 years and reparation and safety mode) Low demand mode: PFDavg in accordance	Yes Yes; green LED Yes; red LED Yes; green LED Yes; red LED Yes; red LED Yes; red LED No Yes 707 V DC (type test) PLe SIL 3
 Wire-break Short-circuit Group error Diagnostics indication LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics Potential separation Potential separation channels between the channels between the channels and backplane bus Isolation Isolation tested with Standards, approvals, certificates Suitable for safety functions Highest safety class achievable in safety mode Performance level according to ISO 13849-1 SIL acc. to IEC 61508 Probability of failure (for service life of 20 years and reparation of the propagation of	Yes Yes Yes; green LED Yes; red LED Yes; green LED Yes; red LED Yes; red LED Yes; red LED No Yes 707 V DC (type test) PLe SIL 3 ir time of 100 hours) < 6.00E-05
 Wire-break Short-circuit Group error Diagnostics indication LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics Potential separation Potential separation channels between the channels between the channels and backplane bus Isolation Isolation tested with Standards, approvals, certificates Suitable for safety functions Highest safety class achievable in safety mode Performance level according to ISO 13849-1 SIL acc. to IEC 61508 Probability of failure (for service life of 20 years and reparation of the probability of failure (for service life of 20 years and reparation of the probability of failure (for service life of 20 years and reparation of the probability of failure (for service life of 20 years and reparation of the probability of failure (for service life of 20 years and reparation of the probability of failure (for service life of 20 years and reparation of the probability of failure (for service life of 20 years and reparation of the probability of failure (for service life of 20 years and reparation of the probability of failure (for service life of 20 years and reparation of the probability of failure (for service life of 20 years and reparation of the probability of failure (for service life of 20 years and reparation of the probability of failure (for service life of 20 years and reparation of the probability of failure (for service life of 20 years and reparation of the probability of failure (for service life of 20 years and reparation of the probability of failure (for service life of 20 years and reparation of the probability of failure (for service life of 20 years and reparation of the probability of failure (for service life of 20 years and reparation of the probability	Yes Yes; green LED Yes; red LED Yes; green LED Yes; red LED Yes; red LED Yes; red LED No Yes 707 V DC (type test) PLe SIL 3 ir time of 100 hours)
 Wire-break Short-circuit Group error Diagnostics indication LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics Potential separation Potential separation channels between the channels between the channels and backplane bus Isolation Isolation tested with Standards, approvals, certificates Suitable for safety functions Highest safety class achievable in safety mode Performance level according to ISO 13849-1 SIL acc. to IEC 61508 Probability of failure (for service life of 20 years and reparation of the propagation of	Yes Yes Yes; green LED Yes; red LED Yes; green LED Yes; red LED Yes; red LED Yes; red LED No Yes 707 V DC (type test) PLe SIL 3 ir time of 100 hours) < 6.00E-05

 $Pobrano\ z:\ https://sterowniki-plc.net/modul-8-wyjsc-binarnych-simatic-s7-1500-siemens-6es7526-2bf00-0ab0$