



SIMATIC S7-1500 analog input module AI 8xU/I HF, up to 24 bit resolution, accuracy 0.1%, 8 channels in groups of 1; common mode voltage: 30 V AC/60 V DC, Diagnostics; Hardware interrupts Measured values scalable, measuring range adjustment, Calibrate in RUN; Delivery including infeed element, shield bracket and shield terminal: Front connector (screw terminals or push-in) to be ordered separately

General information	
Product type designation	AI 8xU/I HF
HW functional status	From FS01
Firmware version	V1.1.0
<ul style="list-style-type: none"> <li>FW update possible</li> </ul>	Yes
Product function	
<ul style="list-style-type: none"> <li>I&amp;M data</li> </ul>	Yes; I&M0 to I&M3
<ul style="list-style-type: none"> <li>Isochronous mode</li> </ul>	No
<ul style="list-style-type: none"> <li>Prioritized startup</li> </ul>	Yes
<ul style="list-style-type: none"> <li>Measuring range scalable</li> </ul>	No
<ul style="list-style-type: none"> <li>Scalable measured values</li> </ul>	Yes
<ul style="list-style-type: none"> <li>Adjustment of measuring range</li> </ul>	Yes
Engineering with	
<ul style="list-style-type: none"> <li>STEP 7 TIA Portal configurable/integrated from version</li> </ul>	V14 / -
<ul style="list-style-type: none"> <li>STEP 7 configurable/integrated from version</li> </ul>	V5.5 SP3 / -
<ul style="list-style-type: none"> <li>PROFIBUS from GSD version/GSD revision</li> </ul>	V1.0 / V5.1
<ul style="list-style-type: none"> <li>PROFINET from GSD version/GSD revision</li> </ul>	V2.3 / -
Operating mode	
<ul style="list-style-type: none"> <li>Oversampling</li> </ul>	No
<ul style="list-style-type: none"> <li>MSI</li> </ul>	Yes
CiR - Configuration in RUN	
Reparameterization possible in RUN	Yes
Calibration possible in RUN	Yes
Supply voltage	
Rated value (DC)	24 V
permissible range, lower limit (DC)	19.2 V
permissible range, upper limit (DC)	28.8 V
Reverse polarity protection	Yes
Input current	
Current consumption, max.	50 mA; with 24 V DC supply
Power	
Power available from the backplane bus	0.85 W
Power loss	
Power loss, typ.	1.9 W
Analog inputs	
Number of analog inputs	8
<ul style="list-style-type: none"> <li>For current measurement</li> </ul>	8
<ul style="list-style-type: none"> <li>For voltage measurement</li> </ul>	8
permissible input voltage for voltage input (destruction limit), max.	28.8 V

permissible input current for current input (destruction limit), max.	40 mA
<b>Input ranges (rated values), voltages</b>	
• 0 to +5 V	No
• 0 to +10 V	No
• 1 V to 5 V	Yes
— Input resistance (1 V to 5 V)	100 kΩ
• -10 V to +10 V	Yes
— Input resistance (-10 V to +10 V)	100 kΩ
• -2.5 V to +2.5 V	Yes
— Input resistance (-2.5 V to +2.5 V)	100 kΩ
• -25 mV to +25 mV	No
• -250 mV to +250 mV	No
• -5 V to +5 V	Yes
— Input resistance (-5 V to +5 V)	100 kΩ
• -50 mV to +50 mV	No
• -500 mV to +500 mV	No
• -80 mV to +80 mV	No
<b>Input ranges (rated values), currents</b>	
• 0 to 20 mA	Yes
— Input resistance (0 to 20 mA)	25 Ω; Plus approx. 42 ohms for overvoltage protection by PTC
• -20 mA to +20 mA	Yes
— Input resistance (-20 mA to +20 mA)	25 Ω; Plus approx. 42 ohms for overvoltage protection by PTC
• 4 mA to 20 mA	Yes
— Input resistance (4 mA to 20 mA)	25 Ω; Plus approx. 42 ohms for overvoltage protection by PTC
<b>Input ranges (rated values), thermocouples</b>	
• Type B	No
• Type C	No
• Type E	No
• Type J	No
• Type K	No
• Type L	No
• Type N	No
• Type R	No
• Type S	No
• Type T	No
• Type TXK/TXK(L) to GOST	No
<b>Input ranges (rated values), resistance thermometer</b>	
• Cu 10	No
• Cu 10 according to GOST	No
• Cu 50	No
• Cu 50 according to GOST	No
• Cu 100	No
• Cu 100 according to GOST	No
• Ni 10	No
• Ni 10 according to GOST	No
• Ni 100	No
• Ni 100 according to GOST	No
• Ni 1000	No
• Ni 1000 according to GOST	No
• LG-Ni 1000	No
• Ni 120	No
• Ni 120 according to GOST	No
• Ni 200	No
• Ni 200 according to GOST	No
• Ni 500	No
• Ni 500 according to GOST	No
• Pt 10	No
• Pt 10 according to GOST	No
• Pt 50	No
• Pt 50 according to GOST	No
• Pt 100	No
• Pt 100 according to GOST	No
• Pt 1000	No

<ul style="list-style-type: none"> <li>• Pt 1000 according to GOST</li> </ul>	No
<ul style="list-style-type: none"> <li>• Pt 200</li> </ul>	No
<ul style="list-style-type: none"> <li>• Pt 200 according to GOST</li> </ul>	No
<ul style="list-style-type: none"> <li>• Pt 500</li> </ul>	No
<ul style="list-style-type: none"> <li>• Pt 500 according to GOST</li> </ul>	No
<b>Input ranges (rated values), resistors</b>	
<ul style="list-style-type: none"> <li>• 0 to 150 ohms</li> </ul>	No
<ul style="list-style-type: none"> <li>• 0 to 300 ohms</li> </ul>	No
<ul style="list-style-type: none"> <li>• 0 to 600 ohms</li> </ul>	No
<ul style="list-style-type: none"> <li>• 0 to 3000 ohms</li> </ul>	No
<ul style="list-style-type: none"> <li>• 0 to 6000 ohms</li> </ul>	No
<ul style="list-style-type: none"> <li>• PTC</li> </ul>	No
<b>Cable length</b>	
<ul style="list-style-type: none"> <li>• shielded, max.</li> </ul>	800 m
<b>Analog value generation for the inputs</b>	
<b>Integration and conversion time/resolution per channel</b>	
<ul style="list-style-type: none"> <li>• Resolution with overrange (bit including sign), max.</li> </ul>	24 bit; When using the function "Scaling of the measured values" or "Measuring range adaptation" (32 bit REAL format); 16 bit when using the S7 format (16 bit INTEGER)
<ul style="list-style-type: none"> <li>• Integration time, parameterizable</li> </ul>	Yes
<ul style="list-style-type: none"> <li>• Integration time (ms)</li> </ul>	Fast mode: 2.5 / 16.67 / 20 / 100 ms, standard mode: 7.5 / 50 / 60 / 300 ms
<ul style="list-style-type: none"> <li>• Basic conversion time, including integration time (ms)</li> </ul>	Fast mode: 4 / 18 / 22 / 102 ms; Standard mode: 9 / 52 / 62 / 302 ms
<ul style="list-style-type: none"> <li>• Interference voltage suppression for interference frequency f1 in Hz</li> </ul>	400 / 60 / 50 / 10 Hz
<ul style="list-style-type: none"> <li>• Basic execution time of the module (all channels released)</li> </ul>	Corresponds to the channel with the highest basic conversion time
<b>Smoothing of measured values</b>	
<ul style="list-style-type: none"> <li>• parameterizable</li> </ul>	Yes
<ul style="list-style-type: none"> <li>• Step: None</li> </ul>	Yes
<ul style="list-style-type: none"> <li>• Step: low</li> </ul>	Yes
<ul style="list-style-type: none"> <li>• Step: Medium</li> </ul>	Yes
<ul style="list-style-type: none"> <li>• Step: High</li> </ul>	Yes
<b>Encoder</b>	
<b>Connection of signal encoders</b>	
<ul style="list-style-type: none"> <li>• for voltage measurement</li> </ul>	Yes
<ul style="list-style-type: none"> <li>• for current measurement as 2-wire transducer</li> </ul>	Yes; with external transmitter supply
<ul style="list-style-type: none"> <li>• for current measurement as 4-wire transducer</li> </ul>	Yes
<ul style="list-style-type: none"> <li>• for resistance measurement with two-wire connection</li> </ul>	No
<ul style="list-style-type: none"> <li>• for resistance measurement with three-wire connection</li> </ul>	No
<ul style="list-style-type: none"> <li>• for resistance measurement with four-wire connection</li> </ul>	No
<b>Errors/accuracies</b>	
Linearity error (relative to input range), (+/-)	0.02 %
Temperature error (relative to input range), (+/-)	0.005 %/K
Crosstalk between the inputs, max.	-80 dB
Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)	0.02 %
note regarding accuracy	at temperatures below 0 °C, the figures for operating error and temperature error are doubled
<b>Operational error limit in overall temperature range</b>	
<ul style="list-style-type: none"> <li>• Voltage, relative to input range, (+/-)</li> </ul>	0.1 %
<ul style="list-style-type: none"> <li>• Current, relative to input range, (+/-)</li> </ul>	0.1 %
<b>Basic error limit (operational limit at 25 °C)</b>	
<ul style="list-style-type: none"> <li>• Voltage, relative to input range, (+/-)</li> </ul>	0.05 %
<ul style="list-style-type: none"> <li>• Current, relative to input range, (+/-)</li> </ul>	0.05 %
<b>Interference voltage suppression for <math>f = n \times (f1 \pm 1 \%)</math>, <math>f1 =</math> interference frequency</b>	
<ul style="list-style-type: none"> <li>• Series mode interference (peak value of interference &lt; rated value of input range), min.</li> </ul>	80 dB; in the Standard operating mode, 40 dB in the Fast operating mode
<ul style="list-style-type: none"> <li>• Common mode voltage, max.</li> </ul>	60 V DC/30 V AC
<ul style="list-style-type: none"> <li>• Common mode interference, min.</li> </ul>	80 dB
<b>Interrupts/diagnostics/status information</b>	

Diagnostics function	Yes
<b>Alarms</b>	
<ul style="list-style-type: none"> <li>• Diagnostic alarm</li> <li>• Limit value alarm</li> </ul>	<p>Yes</p> <p>Yes; two upper and two lower limit values in each case</p>
<b>Diagnoses</b>	
<ul style="list-style-type: none"> <li>• Monitoring the supply voltage</li> <li>• Wire-break</li> <li>• Overflow/underflow</li> </ul>	<p>Yes</p> <p>Yes; only for 1 ... 5 V and 4 ... 20 mA</p> <p>Yes</p>
<b>Diagnostics indication LED</b>	
<ul style="list-style-type: none"> <li>• RUN LED</li> <li>• ERROR LED</li> <li>• Monitoring of the supply voltage (PWR-LED)</li> <li>• Channel status display</li> <li>• for channel diagnostics</li> <li>• for module diagnostics</li> </ul>	<p>Yes; green LED</p> <p>Yes; red LED</p> <p>Yes; green LED</p> <p>Yes; green LED</p> <p>Yes; red LED</p> <p>Yes; red LED</p>
<b>Potential separation</b>	
<b>Potential separation channels</b>	
<ul style="list-style-type: none"> <li>• between the channels</li> <li>• between the channels, in groups of</li> <li>• between the channels and backplane bus</li> <li>• between the channels and the power supply of the electronics</li> </ul>	<p>Yes</p> <p>1</p> <p>Yes</p> <p>Yes</p>
<b>Permissible potential difference</b>	
between different circuits	60 V DC/30 V AC; insulation rated for 120 V AC basic insulation: between the channels and the supply voltage L+; between the channels and the backplane bus; between the channels
<b>Isolation</b>	
Isolation tested with	2 000 V DC between the channels and the supply voltage L+; 2 000 V DC between the channels and the backplane bus; 2 000 V DC between the channels; 707 V DC (type test) between the supply voltage L+ and the backplane bus
<b>Ambient conditions</b>	
<b>Ambient temperature during operation</b>	
<ul style="list-style-type: none"> <li>• horizontal installation, min.</li> <li>• horizontal installation, max.</li> <li>• vertical installation, min.</li> <li>• vertical installation, max.</li> </ul>	<p>-30 °C; From FS02</p> <p>60 °C</p> <p>-30 °C; From FS02</p> <p>40 °C</p>
<b>Dimensions</b>	
Width	35 mm
Height	147 mm
Depth	129 mm
<b>Weights</b>	
Weight, approx.	280 g