



Figure similar

SIMATIC S7-1500 Analog input module AI 8xU/I HS, 16 bit resolution, Accuracy 0.3% 8 channels in groups of 8; Common mode voltage 10 V; Diagnostics; Hardware interrupts 8 channels in 0.0625 ms Oversampling; Delivery including infeed element, shield bracket and shield terminal: Front connector (screw terminals or push-in) to be ordered separately

General information	
Product type designation	AI 8xU/I HS
HW functional status	From FS01
Firmware version	V2.1.0
<ul style="list-style-type: none"> FW update possible 	Yes
Product function	
<ul style="list-style-type: none"> I&M data 	Yes; I&M0 to I&M3
<ul style="list-style-type: none"> Isochronous mode 	Yes
<ul style="list-style-type: none"> Prioritized startup 	Yes
<ul style="list-style-type: none"> Measuring range scalable 	No
<ul style="list-style-type: none"> Scalable measured values 	No
<ul style="list-style-type: none"> Adjustment of measuring range 	No
Engineering with	
<ul style="list-style-type: none"> STEP 7 TIA Portal configurable/integrated from version 	V14 / -
<ul style="list-style-type: none"> STEP 7 configurable/integrated from version 	V5.5 SP3 / -
<ul style="list-style-type: none"> PROFIBUS from GSD version/GSD revision 	V1.0 / V5.1
<ul style="list-style-type: none"> PROFINET from GSD version/GSD revision 	V2.3 / -
Operating mode	
<ul style="list-style-type: none"> Oversampling 	Yes
<ul style="list-style-type: none"> MSI 	Yes
CiR - Configuration in RUN	
Reparameterization possible in RUN	Yes
Calibration possible in RUN	Yes
Supply voltage	
Rated value (DC)	24 V
permissible range, lower limit (DC)	19.2 V
permissible range, upper limit (DC)	28.8 V
Reverse polarity protection	Yes
Input current	
Current consumption, max.	240 mA; with 24 V DC supply
Encoder supply	
24 V encoder supply	
<ul style="list-style-type: none"> Short-circuit protection 	Yes
<ul style="list-style-type: none"> Output current, max. 	20 mA; Max. 47 mA per channel for a duration < 10 s
Power	
Power available from the backplane bus	1.15 W
Power loss	
Power loss, typ.	3.4 W

Analog inputs

Number of analog inputs	8
<ul style="list-style-type: none"> • For current measurement • For voltage measurement 	8
permissible input voltage for voltage input (destruction limit), max.	28.8 V
permissible input current for current input (destruction limit), max.	40 mA
Input ranges (rated values), voltages	
<ul style="list-style-type: none"> • 0 to +5 V • 0 to +10 V • 1 V to 5 V <ul style="list-style-type: none"> — Input resistance (1 V to 5 V) • -10 V to +10 V <ul style="list-style-type: none"> — Input resistance (-10 V to +10 V) • -2.5 V to +2.5 V • -25 mV to +25 mV • -250 mV to +250 mV • -5 V to +5 V <ul style="list-style-type: none"> — Input resistance (-5 V to +5 V) • -50 mV to +50 mV • -500 mV to +500 mV • -80 mV to +80 mV 	<p>No</p> <p>No</p> <p>Yes</p> <p>50 kΩ</p> <p>Yes</p> <p>100 kΩ</p> <p>No</p> <p>No</p> <p>No</p> <p>Yes</p> <p>50 kΩ</p> <p>No</p> <p>No</p> <p>No</p>
Input ranges (rated values), currents	
<ul style="list-style-type: none"> • 0 to 20 mA <ul style="list-style-type: none"> — Input resistance (0 to 20 mA) • -20 mA to +20 mA <ul style="list-style-type: none"> — Input resistance (-20 mA to +20 mA) • 4 mA to 20 mA <ul style="list-style-type: none"> — Input resistance (4 mA to 20 mA) 	<p>Yes</p> <p>41 Ω; Plus approx. 42 ohms for overvoltage protection by PTC</p> <p>Yes</p> <p>41 Ω; Plus approx. 42 ohms for overvoltage protection by PTC</p> <p>Yes</p> <p>41 Ω; Plus approx. 42 ohms for overvoltage protection by PTC</p>
Input ranges (rated values), thermocouples	
<ul style="list-style-type: none"> • Type B • Type C • Type E • Type J • Type K • Type L • Type N • Type R • Type S • Type T • Type TXK/TXK(L) to GOST 	<p>No</p> <p>No</p> <p>No</p> <p>No</p> <p>No</p> <p>No</p> <p>No</p> <p>No</p> <p>No</p> <p>No</p> <p>No</p>
Input ranges (rated values), resistance thermometer	
<ul style="list-style-type: none"> • Cu 10 • Cu 10 according to GOST • Cu 50 • Cu 50 according to GOST • Cu 100 • Cu 100 according to GOST • Ni 10 • Ni 10 according to GOST • Ni 100 • Ni 100 according to GOST • Ni 1000 • Ni 1000 according to GOST • LG-Ni 1000 • Ni 120 • Ni 120 according to GOST • Ni 200 • Ni 200 according to GOST • Ni 500 • Ni 500 according to GOST • Pt 10 • Pt 10 according to GOST 	<p>No</p> <p>No</p> <p>No</p> <p>No</p> <p>No</p> <p>No</p> <p>No</p> <p>No</p> <p>No</p> <p>No</p> <p>No</p> <p>No</p> <p>No</p> <p>No</p> <p>No</p> <p>No</p> <p>No</p> <p>No</p> <p>No</p> <p>No</p>

• Pt 50	No
• Pt 50 according to GOST	No
• Pt 100	No
• Pt 100 according to GOST	No
• Pt 1000	No
• Pt 1000 according to GOST	No
• Pt 200	No
• Pt 200 according to GOST	No
• Pt 500	No
• Pt 500 according to GOST	No
Input ranges (rated values), resistors	
• 0 to 150 ohms	No
• 0 to 300 ohms	No
• 0 to 600 ohms	No
• 0 to 3000 ohms	No
• 0 to 6000 ohms	No
• PTC	No
Cable length	
• shielded, max.	800 m
Analog value generation for the inputs	
Integration and conversion time/resolution per channel	
• Resolution with overrange (bit including sign), max.	16 bit
• Basic execution time of the module (all channels released)	62.5 µs; independent of number of activated channels
Smoothing of measured values	
• parameterizable	Yes
• Step: None	Yes
• Step: low	Yes
• Step: Medium	Yes
• Step: High	Yes
Encoder	
Connection of signal encoders	
• for voltage measurement	Yes
• for current measurement as 2-wire transducer — Burden of 2-wire transmitter, max.	Yes 820 Ω
• for current measurement as 4-wire transducer	Yes
• for resistance measurement with two-wire connection	No
• for resistance measurement with three-wire connection	No
• for resistance measurement with four-wire connection	No
Errors/accuracies	
Linearity error (relative to input range), (+/-)	0.02 %
Temperature error (relative to input range), (+/-)	0.005 %/K
Crosstalk between the inputs, max.	-60 dB
Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)	0.02 %
Operational error limit in overall temperature range	
• Voltage, relative to input range, (+/-)	0.3 %
• Current, relative to input range, (+/-)	0.3 %
Basic error limit (operational limit at 25 °C)	
• Voltage, relative to input range, (+/-)	0.2 %
• Current, relative to input range, (+/-)	0.2 %
Interference voltage suppression for $f = n \times (f_1 \pm 1 \%)$, f_1 = interference frequency	
• Common mode voltage, max.	10 V
• Common mode interference, min.	50 dB at 400 Hz; 60 dB at 60 / 50 / 10 Hz
Isochronous mode	
Filtering and processing time (TCI), min.	80 µs
Bus cycle time (TDP), min.	250 µs
Interrupts/diagnostics/status information	
Diagnostics function	Yes
Alarms	
• Diagnostic alarm	Yes

• Limit value alarm	Yes; two upper and two lower limit values in each case
Diagnoses	
• Monitoring the supply voltage	Yes
• Wire-break	Yes; only for 1 ... 5 V and 4 ... 20 mA
• Overflow/underflow	Yes
Diagnostics indication LED	
• RUN LED	Yes; green LED
• ERROR LED	Yes; red LED
• Monitoring of the supply voltage (PWR-LED)	Yes; green LED
• Channel status display	Yes; green LED
• for channel diagnostics	Yes; red LED
• for module diagnostics	Yes; red LED
Potential separation	
Potential separation channels	
• between the channels	No
• between the channels, in groups of	8
• between the channels and backplane bus	Yes
• between the channels and the power supply of the electronics	Yes
Permissible potential difference	
between the inputs (UCM)	20 V DC
Between the inputs and MANA (UCM)	10 V DC
Isolation	
Isolation tested with	707 V DC (type test)
Ambient conditions	
Ambient temperature during operation	
• horizontal installation, min.	-25 °C; From FS02
• horizontal installation, max.	60 °C
• vertical installation, min.	-25 °C; From FS02
• vertical installation, max.	40 °C
Altitude during operation relating to sea level	
• Installation altitude above sea level, max.	5 000 m; Restrictions for installation altitudes > 2 000 m, see manual
Dimensions	
Width	35 mm
Height	147 mm
Depth	129 mm
Weights	
Weight, approx.	300 g