



MATERIAL FACT SHEET

231491 FX3U-128MR/ES

General Data

Product Hierarchy	IAD213
	Compact PLC
	FX3U
Ext. Material Group	10 STANDARD ITEM
ABC Indicator	B (Limited Availability from Stock)

FA-COM PLC: Main Unit

Series	MELSEC-F SERIES
Type	FX3U
Power Supply (V)	100-240
Current Type	AC
Program Memory	64K STEPS
Program Memory Unit	RAM
Integrated Digital Inputs	64
Integrated Digital Outputs	64
Output Type	RELAY
Local I/O Points	256
Local + Remote I/O Points	384
Expandable	YES
Cycle Time LD (ns)	65
Cycle Time MOV (ns)	642
USB	OPTION
RS-422	1
Power Consumption (W)	65
Buffer Battery	YES
Protection Class	IP10
Min. Ambient Temperature (°C)	0
Max. Ambient Temperature (°C)	55

Product Dimensions & Weight

Width (mm)	350
Height (mm)	90
Depth (mm)	86
Weight (kg)	1,8

Logistic Dimensions & Gross Weight

Length (cm)	41,5
Width (cm)	12,5
Height (cm)	11,5
Gross Weight (kg)	1,920
Volume (cdm)	5,966

Stock Data

Planned Delivery Time (Days)	296
------------------------------	-----

Life Cycle

Sales Start	18.03.2010
Predecessor	206141 / FX3U-128MR/ES

Additional Product Information

Binding Tariff Information	DEBTI-10854/21-1
BTI validity date	10.10.2024
Battery included	YES – CHECK SPARE PART LIST

Export Data

Commodity Code	85371091
Legal Control (Dual Use List)	Not Listed
Country of Origin	Japan (JP)
Preference Status (Supplier Declaration)	Non EU

Environmental

REACH Limit Exceeded	NO
Dangerous Goods Class	NO
Dangerous Goods Identifier	NO
RoHS Compliance	COMPLIANT
WEEE	B2B

Conformity

CE	COMPLIANT
UL/cUL	COMPLIANT
EAC	COMPLIANT
Shipping Approvals	ABS,BV,DNV GL,KR,LR,NK,RINA
UKCA	COMPLIANT

Product Packaging

Cardboard (g)	237
Other paper (g)	0
Aluminum (g)	0
Steel (g)	0
Styrofoam (g)	0
Other plastic (g)	0
Wood (g)	0
Glass (g)	0
Others (g)	0

Spare parts

Material	Description	Quantity	Unit
<u>220174</u>	FX3U-128M COVER TOP	1	PC
<u>87373</u>	FX2N/FX3U 64/128 TERM BLOCK 42 PIN	1	PC
<u>87375</u>	FX2N/FX3U 32/80 ALL TERM BLOCK 24 PIN	1	PC
158989	FX1S/FX1N/FX3U DIN RAIL SLIDER	1	PC
<u>211781</u>	FX3U-128MT/ES PCB I/O	1	PC
211782	FX3U-128MT/ESS I/O BOARD	1	PC
<u>211783</u>	FX3U16/32/48/64/80/128 PCB IF	1	PC
<u>211786</u>	FX3U-128MR/MT/ES/ESS PCB POWER	1	PC
211798	FX3U-128 TERMINAL COVER	1	PC
212451	FX3U-128MR/ES BODY COVER	1	PC
212452	FX3U-128MT/ES BODY COVER	1	PC
212453	FX3U-128MT/ESS BODY COVER	1	PC
212462	FX3U-48/64/80/128 FUSE	1	PC
<u>212463</u>	FX1N/FX1S/FX3U/FX5U Output Relay	1	PC
<u>212464</u>	FX3S/FX3U TRANSISTOR	1	PC
<u>165286</u>	FX3U-32BL	1	PC
210200	FX3U CAP P.P. Adaptor, Connector	1	PC
210262	FX3U-128MR/MT ALL Case S Assy Body Case	1	PC
<u>210278</u>	FX3U-16-128MR/MT ALL COVER BD COVER	1	PC
210279	FX3U-16-128MR/MT ALL Cover Battery Cove	1	PC
<u>210280</u>	FX3U-16-128MR/MT ALL COVER EXT COVER	1	PC
211745	FX3U-16-128MR/MT ADAPTOR COVER	1	PC
211753	FX3U-FLROM-16/64 MEMORY COVER	1	PC
211754	FX3U-232-BD COVER	1	PC
211755	FX3U-485-BD COVER	1	PC
211756	FX3U-USB-BD COVER	1	PC
211758	FX3U-FLROM-64L MEMORY COVER	1	PC
<u>211762</u>	FX3U-48 PCB CPU	1	PC

Material	Description	Quantity	Unit
211764	FX3U-128 PCB CPU	1	PC
211765	FX3U-128MR/ES I/O BOARD	1	PC

Compatible products

Material	Description / Price List Text / Classification
31870	FX-20P-CADP GOT FX Series Adapter cable; 0.3 m Class 100100110: FA-COM PLC: Cable
45348	FX0N-65EC PLC, FX Series Connection Cable for Base and Extension units FX0N/FX2N, 0.65m Class 100100110: FA-COM PLC: Cable
70880	FX2N-CNV-BC PLC, FX2N Adapter for FX extension or special function modules Class 100100111: FA-COM PLC: Other Option
76094	FX-422CAB0 RS422 connection cable for FX0/0S/0N/2N Class 100100110: FA-COM PLC: Cable
159642	FX-232AWC-H RS-422/RS-232C converter to connect FX PLC and PC Class 100100111: FA-COM PLC: Other Option
165268	FX3U-7DM PLC, FX Series Display Unit Class 100100111: FA-COM PLC: Other Option
165278	FX3U-FLROM-16 PLC, FX3U Flash-RAM memory cassette; 16k steps PLC program Class 100100111: FA-COM PLC: Other Option
165279	FX3U-FLROM-64 PLC, FX3U Series Flash-RAM memory cassette; 64k steps PLC program Class 100100111: FA-COM PLC: Other Option
165280	FX3U-FLROM-64L PLC, FX3U Flash-RAM memory cassette; 64K steps PLC program; incl. copy function Class 100100111: FA-COM PLC: Other Option
165281	FX3U-232-BD PLC, FX3U RS232C Interface module; for MELSEC FX3U Class 100100107: FA-COM PLC: Serial Com Module
165282	FX3U-422-BD PLC, FX3U RS422 Interface module; for MELSEC FX3U Class 100100107: FA-COM PLC: Serial Com Module
165283	FX3U-485-BD PLC, FX3U RS485 Interface module, 1:n Multidrop, network expansion until 50 m Class 100100107: FA-COM PLC: Serial Com Module
165284	FX3U-USB-BD PLC, FX3U USB Interface module incl. USB cable (3m) Class 100100107: FA-COM PLC: Serial Com Module
165285	FX3U-CNV-BD PLC, FX3U Communication adapter for MELSEC FX3U ADP special function modules Class 100100111: FA-COM PLC: Other Option
165286	FX3U-32BL PLC, FX3U/C Battery Class 100100112: FA-COM PLC: Spare Part
165286	FX3U-32BL PLC, FX3U/C Battery Class 100101303: FA-OTHERS: Battery
165287	FX3U-7DM-HLD PLC, FX Series Panel Mounting Kit for FX3U-7DM incl. 1.5m cable Class 100100111: FA-COM PLC: Other Option
165288	FX-USB-AW PLC, Interface Converter USB/RS422 between PC and MELSEC PLC, 3 m Class 100100111: FA-COM PLC: Other Option
169507	FX3U-1PSU-5V PLC, FX Series Power supply module for 5V bus Class 100100111: FA-COM PLC: Other Option
221271	FX-30P PLC, FX Series Hand-held programming unit Class 100100111: FA-COM PLC: Other Option
230104	FX3U-CF-ADP PLC, FX3U Data logger module; CF card slot; CSV file format Class 100100111: FA-COM PLC: Other Option

Material	Description / Price List Text / Classification
<u>234630</u>	GX Works2 V01-2L0C-E PLC Programming –S/W for MELSEC Q/L/F; USB; 2 PCs Class 100101201: FA-Software: Software PLC
<u>234631</u>	GX Works2 V01-5L0C-E SPS Programming-S/W for Melsec Q/L/F;engl;USB;5 PC´s Class 100101201: FA-Software: Software PLC
<u>237307</u>	FX3U-8AV-BD PLC, FX3U analog setpoint adapter for 8 stpoints Class 100100111: FA-COM PLC: Other Option
<u>244876</u>	GX Works2 V01-2L0C-G PLC Programming S/W for MELSEC Q/L/F Series; German; USB; 2 PCs Class 100101201: FA-Software: Software PLC
<u>244877</u>	GX Works2 V01-5L0C-G PLC Programming –S/W for MELSEC Q/L/F; USB; 5 PCs Class 100101201: FA-Software: Software PLC
<u>245565</u>	FX3U-FLROM-1M SPS, FX3U(C) Memory cassette;1MB Class 100100111: FA-COM PLC: Other Option
<u>248245</u>	FX-20P-CAB0 PLC, FX Series Connection Cable with FX-10P-E/FX-20P-ESET0/FX-10DM-E,1,5m Class 100100110: FA-COM PLC: Cable
<u>261190</u>	FX3U-CNV-BD-BS Class 100100111: FA-COM PLC: Other Option
<u>285598</u>	FX0N-30EC PLC, FX Series Connection Cable for Base and Extension units FX0N/FX2N, 0.30m Class 100100110: FA-COM PLC: Cable
<u>286227</u>	iQ Works V02-2L0C-E iQ Works V2.0;incl Navigator,GX Works,GT Works,MT Works;engl;USB;2 PC´s Class 100101201: FA-Software: Software PLC
<u>286228</u>	iQ Works V02-5L0C-E iQ Works V2.0;incl Navigator,GX Works,GT Works,MT Works;engl;USB;5 PC´s Class 100101201: FA-Software: Software PLC
<u>303426</u>	iQ Works V02-15L0C-E iQ Works V2.0;incl Navigator,GX Works,GT Works,MT Works;engl;USB;15 PC´s Class 100101201: FA-Software: Software PLC
<u>338821</u>	iQ Works V02-2L0C-G iQ Works V2.0;incl Navigator,GX Works,GT Works,MT Works;German;USB;2 PC´s Class 100101201: FA-Software: Software PLC
<u>339022</u>	iQ Works V02-5L0C-G iQ Works V2.0;incl Navigator,GX Works,GT Works,MT Works;German;USB;5 PC´s Class 100101201: FA-Software: Software PLC
<u>401853</u>	iQ Works V02-2L0C-IT iQ Works V2.0;incl Navigator,GX Works,GT Works,MT Works;Italian;USB;2 PCs Class 100101201: FA-Software: Software PLC